

SWITCH BINDINGS FOR SWS KODIAK





SWITCH BINDINGS FOR SWS KODIAK

Circuit breakers

(A:CIRCUIT BREAKER PULLED:x, Bool)

- System index depends on aircraft, reference systems.cfg for exhaustive list

Oxygen

(L:XMLVAR_Oxygen, Bool)

- 0 off
- 1 on

ELT

(L:Switch_ELT_1, Enum)

- 0 test
- 1 off/arm
- 2 on

AUX BUS

(L:XMLVAR_AUX_Bus_ON, Bool)

- 0 off
- 1 on

Reading light switches

(L:SWS_LIGHTING_Switch_Light_Cabin_x, Bool) xE[1,12]

- 0 off
- 1 on
- SWS_LIGHTING_Switch_Light_Cabin_12 is an Enum and controls the CABIN LIGHTING switch on the knee panel. 0 is OFF, 1 is NORMAL, 2 is ON



Tank selectors (overhead)

(L:SWS_Kodiak_TankSelector_x, Bool) xE[1,2]

- 0 closed
- 1 open

Harness levers (overhead)

(L:Lever_Harness_x, Bool) xE[1,2]

- 0 unlocked
- 1 locked

Landing light switch

(L:SWS_LIGHTING_Switch_Light_Landing, Enum)

- 0 off
- 1 pulse
- 2 on

Stall warning

(L:STALL_WARNING, Bool)

- 0 off
- 1 on

Starter switch

(L:SWS_ENGINE_Switch_Starter_ThreeState_1, Enum)

- 0 LO/MOTOR
- 1 Off
- 2 HI START



Ignition switch

(L: SWS_ENGINE_Switch_Ignition_1, Bool)

- 0 off
- 1 on

Fuel pump switch

(L:SWS_FUEL_Switch_Pump_1, Enum)

Potentiometers

(A:LIGHT POTENTIOMETER:x, Percent) x=(2,3,7,11,21)

ESI500

(L:SWS_ESI500_Menu_1, Bool):

- 0: released
- 1: pressed
- When assigning, make sure the assignment is momentary otherwise the menu will toggle all the time

(L:SWS_ESI500_Menu_Option_Change, Enum)

- -1: Go left/decrease altimeter #3. Momentary.
- +1: Go right/increase altimeter #3. Momentary.
- Automatically reset to 0 by code

(L:SWS_ESI500_Menu_Select, Bool)

- 1: Pressed. Will select menu option or toggle back and forth from STD altimeter
- 0: Released.



Cupholders

(L:Cupholder_x, Bool) xE[1,8]

- 0 stowed
- 1 deployed

Armrests

(L:Armrest_x, Bool) xE[1,6]

- 0 stowed
- 1 deployed

